

Stay Connected...
WORLDWIDE.

TravelComm
A WorldCell Company

IRIDIUM



TO REACH WORLDCELL TRAVELCOMM

Please contact WorldCell TravelComm
Customer Care for further help.

Dial: + 1 301 960 0078

Note: (+ character replaces the international access code)
OR

001 301 960 0078

support@travelcomm.us

TO USE/POWER ON THE PHONE:

Prior to Placing a call:

- Prior to making a call, snap and lock the antenna into the **upright** position.
- Extend the antenna to its full length, being sure to keep the antenna pointing **STRAIGHT UP AT THE SKY**.
- Turn on the phone using the red power button. The phone will display several screens and start-up information.
 - If you see "ROTATE ANTENNA" or "ORIENT ANTENNA", make sure the antenna is fully extended and facing upward, and that you have a clear view of the sky.
- Your phone should indicate that it has "REGISTERED". Once connected to the network, the signal strength will be displayed in small bars in the upper right corner. Once you have at least one signal bar, begin dialing.
 - If you see "CALL FAILED", "SYSTEM BUSY", "RESTRICTED AREA", OR "WEAK SIGNAL", try again in a few minutes. The phone will continue trying to connect.

To Place a Call:

Always use the phone outside with a clear view of the sky. Move away from any buildings, tall structures, or trees. Extend the antenna to its full length, being sure to keep the antenna pointing **STRAIGHT UP AT THE SKY**.

- Dial the International prefix of 00 **OR** press and hold the 0/* key to display the + character.
- Enter the country code, followed by the area code and phone number.

Examples:

USA from abroad: dial + 1 301 960 0060
country code area code phone number

- Press the OK button.
- You will hear a series of beeps while the call connects followed by the normal ringing tone indicating your call is being connected.

TO REACH YOU:

Via SMS or Email:

- Go to the Iridium web page: <http://messaging.iridium.com/>
- Type 8816 and your eight-digit Iridium phone number*
- Type the messages and press send. A maximum of 160 characters can be sent. **OR** Send an email to the address following this format: 8816 [your eight-digit Iridium phonenumber]@msg.iridium.com

MESSAGE RETRIEVAL:

When an email or SMS message is received, a small envelope icon will appear on the display screen.

- Press the menu key.
- Using the arrow keys, scroll until the phone display reads "messages", then press OK.
- Select "Read New" or "Read All" and press OK.
- Use the arrow keys to scroll through each message.
- At the end of the message, you will be asked if you would like to "VIEW OPTIONS?". Press OK to scroll through the options.
- To delete messages, press the menu key until "Erase Messages" appears, then press OK.

TO ACCESS VOICEMAIL:

- Press the messages key or manually dial your Iridium phone number as if you were making a regular call, starting with 00: 00 816 [your eight-digit number]
- When prompted, enter your entire phone number again beginning with 8816. **DO NOT** dial 00.
- After you hear the standard greeting, press the star (*) key to interrupt it.
- When prompted, enter you pin number 2355.
- To play your messages, press 1 and follow the voice prompts.

COUNTRY CODES:

Australia	61	Kuwait	965
Austria	43	Lithuania	370
Belgium	32	Luxembourg	352
Brazil	55	Malaysia	60
Canada	1	Mexico	52
Egypt	20	Philippines	63
France	33	Romania	40
Germany	49	Russia	7
Greece	30	Singapore	65
Hungary	36	Switzerland	41
Iceland	354	Taiwan	886
India	91	Thailand	66
Italy	39	United Kingdom	44
Japan	81	United States	1
Jordan	962	Vietnam	84